

ITEM # 34205

Load Resistor Kit:

6 Ohm, 50 Watt Resistors can be connected across the turn signal bulbs to simulate the load of a regular filament bulb (2 Amp load). This will solve LED related turn signal problems such as hyper flashing, no flashing or burnt out bulb indications. One resistor is required for each turn signal bulb. Includes moisture resistance splice taps.

Connection Instructions:

Using included splice taps, connect one wire to ground and the other wire to the turn/brake wire. You do not have to cut your car's wires. Squeeze splice taps with pliers. One Load Resistor is required for each turn signal bulb.

Warning:

The Load Resistor produces a lot of heat. Must be installed with no contact to paint, plastic, or combustible materials.

